

TB74 Protocol for RS232 104U / Pulse

JMD Support bill 50、100、500、1000、5000 (Jamaica)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
★	1 Pulse / JMD 50	OFF	OFF	OFF							
	2 Pulse / JMD 50	OFF	OFF	ON							
	3 Pulse / JMD 50	OFF	ON	OFF							
	4 Pulse / JMD 50	OFF	ON	ON							
	5 Pulse / JMD 50	ON	OFF	OFF							
	10 Pulse / JMD 50	ON	OFF	ON							
	20 Pulse / JMD 50	ON	ON	OFF							
	100 Pulse / JMD 50	ON	ON	ON							
	Fast Output Pulse	Lo=50ms Hi=100ms			ON						
★	Slow Output Pulse	Lo=50ms Hi=300ms			OFF						
	Inhibit level Active Low					ON					
★	Inhibit level Active High					OFF					
★	Accept JMD 50						ON				
	Reject JMD 50						OFF				
★	Accept JMD 100							ON			
	Reject JMD 100							OFF			
★	Accept JMD 500								ON		
	Reject JMD 500								OFF		
★	Accept JMD 1000									ON	
	Reject JMD 1000									OFF	
★	Accept JMD5000										ON
	Reject JMD5000										OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.

DIP SW SETTING : 2

FUNCTION		SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol		ON		
	RS232 Protocol		OFF		
	Reserved			ON	
★	Reserved			OFF	
	Reserved				ON
★	Reserved				OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch