



TP70P3B/P5 Protocol for RS232 104U / Pulse

MYR6 Support bill 1 、 5 、 10 、 20 、 50 、 100 (Malaysia)

DIP SW SETTING : 1

| FUNCTION | | SW1 | SW2 | SW3 | SW4 | SW5 | SW6 | SW7 | SW8 | SW9 | SW10 |
|----------|---------------------------|---------------------|-----|-----|-----|-----|-----|-----|-----|-----|------|
| ★ | 1 Pulse / MYR 1 | OFF | OFF | OFF | | | | | | | |
| | 2 Pulse / MYR 1 | OFF | OFF | ON | | | | | | | |
| | 3 Pulse / MYR 1 | OFF | ON | OFF | | | | | | | |
| | 4 Pulse / MYR 1 | OFF | ON | ON | | | | | | | |
| | 5 Pulse / MYR 1 | ON | OFF | OFF | | | | | | | |
| | 10 Pulse / MYR 1 | ON | OFF | ON | | | | | | | |
| | 20 Pulse / MYR 1 | ON | ON | OFF | | | | | | | |
| | 100 Pulse / MYR 1 | ON | ON | ON | | | | | | | |
| | Fast Output Pulse | Lo=50ms Hi=100ms | | | ON | | | | | | |
| ★ | Slow Output Pulse | Lo=50ms Hi=300ms | | | OFF | | | | | | |
| | Inhibit level Active Low | | | | | ON | | | | | |
| ★ | Inhibit level Active High | | | | | OFF | | | | | |
| ★ | Accept MYR 1 | | | | | | ON | | | | |
| | Reject MYR 1 | | | | | | OFF | | | | |
| ★ | Accept MYR 5 | | | | | | | ON | | | |
| | Reject MYR 5 | | | | | | | OFF | | | |
| ★ | Accept MYR 10 | | | | | | | | ON | | |
| | Reject MYR 10 | | | | | | | | OFF | | |
| ★ | Accept MYR 20 | | | | | | | | | ON | |
| | Reject MYR 20 | | | | | | | | | OFF | |
| ★ | Accept MYR 50 & 100 | | | | | | | | | | ON |
| | Reject MYR 50 & 100 | | | | | | | | | | OFF |

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.

DIP SW SETTING : 2

| FUNCTION | SW1 | SW2 | SW3 | SW4 |
|--------------------------|-----|-----|-----|-----|
| ★ Pulse Normal High (NO) | ON | | | |
| Pulse Normal Low (NC) | OFF | | | |
| ★ Pulse Protocol | | ON | | |
| RS232 Protocol | | OFF | | |
| Straight | | | ON | |
| ★ Turn Over | | | OFF | |
| Reserved | | | | ON |
| ★ Reserved | | | | OFF |

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.

Currency Assign Data

| Interface / Bill value | ICT | Pulse |
|------------------------|-----|-------|
| BV1 | 1 | 1 |
| BV2 | 5 | 5 |
| BV3 | 10 | 10 |
| BV4 | 20 | 20 |
| BV5 | 50 | 50 |
| BV6 | 100 | 100 |