



TP70P3B/P5 Protocol for RS232 004 / Pulse

SAR4 Support bill 1 、 5 、 10 、 50 (Saudi_Arabia)

DIP SW SETTING : 1

FUNCTION		SW1	SW2	SW3	SW4	SW5	SW6	SW7	SW8	SW9	SW10
Normal Pulse	Special Pulse										
★ 1 Pulse / SAR 1	3 Pulse / SAR 5	OFF	OFF	OFF							
2 Pulse / SAR 1	6 Pulse / SAR 5	OFF	OFF	ON							
3 Pulse / SAR 1	9 Pulse / SAR 5	OFF	ON	OFF							
4 Pulse / SAR 1	12 Pulse / SAR 5	OFF	ON	ON							
5 Pulse / SAR 1	15 Pulse / SAR 5	ON	OFF	OFF							
10 Pulse / SAR 1	30 Pulse / SAR 5	ON	OFF	ON							
20 Pulse / SAR 1	60 Pulse / SAR 5	ON	ON	OFF							
100 Pulse / SAR 1	300 Pulse / SAR 5	ON	ON	ON							
Fast Output Pulse	Lo=50ms Hi=100ms				ON						
★ Slow Output Pulse	Lo=50ms Hi=300ms				OFF						
Inhibit level Active Low						ON					
★ Inhibit level Active High						OFF					
★ Accept SAR 1 (Note 3)							ON				
Reject SAR 1 (Note 3)							OFF				
★ Accept SAR 5								ON			
Reject SAR 5								OFF			
★ Accept SAR 10									ON		
Reject SAR 10									OFF		
★ Accept SAR 50										ON	
Reject SAR 50										OFF	
★ Reserved											ON
Reserved											OFF

★ Default setting

Note: (1) Please reset the bill acceptor after any changes on Dip switch.

(2) Dip Switch 1 to 5 are only for Pulse mode.

(3) SW6

Set ON, Accept 1 SAR (Normal Pulse)	
Pulse	ICT
SAR 1 = 1 pulse	SAR 1 = 40
SAR 5 = 5 pulse	SAR 5 = 41
SAR 10 = 10 pulse	SAR 10 = 42
SAR 50 = 50 pulse	SAR 50 = 43

Set OFF, Reject 1 SAR (Special Pulse)	
Pulse	ICT
SAR 5 = 1 pulse	SAR 5 = 40
SAR 10 = 2 pulse	SAR 10 = 41
SAR 50 = 50 pulse	SAR 50 = 42

DIP SW SETTING : 2

	FUNCTION	SW1	SW2	SW3	SW4
★	Pulse Normal High (NO)	ON			
	Pulse Normal Low (NC)	OFF			
★	Pulse Protocol		ON		
	RS232 Protocol		OFF		
	Straight			ON	
★	Turn Over			OFF	
	Special Pulse				ON
★	Normal Pulse				OFF

★ Default setting

Note: Please reset the bill acceptor after any changes on Dip switch.